

DESCRIPTION

Copper SB

Charging power up to 22kW (3 Phase)

Compatible with all Type 1 and Type 2 electric cars

Technical information

Connector type: Socket

Maximum current: 32 A, 5x10 mm² cable

DC Leakage protection Included: Yes

User interface: myWallbox Portal, Wallbox App

Overvoltage Category: CAT III

Storage temperature: From -40°C to 70°C

RCCB: Requires an external RCCB

Nominal frequency: 50 Hz / 60 Hz

Degree of protection: IP54 / IK08

Operating temperature From -25 °C to 40 °C

Input voltage: 110 / 230 V AC ± 10% (1P) / 400 V AC ± 10% (3P)

Included features: Power Sharing Smart

Dimensions: 260x192x113 mm

Charging power : 22kW

Charging mode Mode 3

Charger status information: Wallbox App, myWallbox Portal, RGB LED, Pantalla de 10.9 cm (4.3")

Cable length: 5m

Important note

If you are a Renault Zoe I (2015 edition) user, please keep in mind that this model is only compatible with this charger for single-phase charging (up to 7.4kW).

The Renault Zoe II (2018 edition), ordered after the 19th of March 2018, is perfectly compatible with this charger for both single-phase and three-phase charging (up to 22kW).

Charging cable holder

Wallbox charging cable holder compatible with Commander 2, Copper SB, Pulsar Plus and Pulsar chargers.



Charging cable with connector, 5 meters length, compatible with all electric cars and chargers with Type 2 connector.

- This charging cable is compatible with all electric cars and chargers with Type 2 connector
- Charging power up to 22 kW
- Cable length 5 m
- Charging cable Mode 3
- Single-phase and three-phase AC cable
- Includes covers for connectors
- Compatible with Copper SB, KSIX EVHome+ SC and all public applications with Type 2 socket

TECHNICAL SPECIFICATIONS.

Color	Black
Degree of protection	IP54
Power	22kW
Connector type	Type 2
Impact resistance	IK08
Power Sharing	Yes
Wifi	Yes
Measures	260 x 192 x 113 mm

STRENGTHS