

DESCRIPTION

Copper SB

Charging power up to 22kW (3 Phase)

Compatible with all Type 1 and Type 2 electric cars

Technical information

Connector type: Socket

Maximum current: 32 A, 5x10 mm² cable

DC Leakage protection Included: Yes

User interface: myWallbox Portal, Wallbox App

Overvoltage Category: CAT III

Storage temperature: From -40°C to 70°C

RCCB: Requires an external RCCB

Nominal frequency: 50 Hz / 60 Hz

Degree of protection: IP54 / IK08

Operating temperature From -25 °C to 40 °C

Input voltage: 110 / 230 V AC ± 10% (1P) / 400 V AC ± 10% (3P)

Included features: Power Sharing Smart

Dimensions: 260x192x113 mm

Charging power : 22kW

Charging mode Mode 3

Charger status information: Wallbox App, myWallbox Portal, RGB LED, Pantalla de 10.9 cm (4.3")

Cable length: Not included


Important note

If you are a Renault Zoe I (2015 edition) user, please keep in mind that this model is only compatible with this charger for single-phase charging (up to 7.4kW).

The Renault Zoe II (2018 edition), ordered after the 19th of March 2018, is perfectly compatible with this charger for both single-phase and three-phase charging (up to 22kW).

Charging cable holder

Wallbox charging cable holder compatible with Commander 2, Copper SB, Pulsar Plus and Pulsar chargers.



TECHNICAL SPECIFICATIONS.

Color	Black
Degree of protection	IP54
Power	22kW
Connector type	Type 2
Impact resistance	IK08
Power Sharing	Yes
Bluetooth	yes
Wifi	Yes
Ethernet	yes
3G/4G	yes
Measures	260 x 192 x 113 mm
OCPP	yes

STRENGTHS